

Adaptive Paging Signal in Cordless Telephone

Field of the Invention:

This application is related to the field of cordless telephony, and more particularly
5 to a paging feature that enables a user to locate a misplaced cordless telephone handset.

Background of the Invention:

Cordless telephones are made up of a base unit, which is traditionally connected
to a telephone wall outlet and to an AC power outlet, and is thus fixed in location, and a
10 portable handset. The handset is normally in one of two positions. In a first position, the
handset is coupled to the base unit, such as by being cradled thereto, and is normally
receiving charging power from the base unit through a set of charge contacts. When in
this position, the telephone is in an on-hook condition, i.e., is not connected to the central
office or to another telephone or otherwise engaged in telephony activities.

15 In a second position, the handset is de-coupled from the base unit and is capable
of communicating with the base unit through RF communications. When in this position,
the telephone may be in either an on-hook condition or an off-hook condition. When in
the off-hook condition, a user engages in telephony activities by using the handset. The
handset maintains an RF link with the base unit, and the base unit establishes wired
20 connection to the central office and the public switched telephone network (or to an
internet service provider based network or any other form of network).

The major advantage of cordless telephones, when compared to traditional wired
telephones, is that cordless telephones do not require the user to remain at one given

location while engaged in telephony activities. Instead, the user is able to roam within range of the base unit, and as long as the handset is within range, the user can engage in telephony activities such as initiating outgoing telephone calls and receiving incoming telephone calls. Typically, as cordless telephone technology advances, the range of the RF link between the base and handset continues to increase. This is partly due to the use of higher powered RF frequencies which are allowed due to the use of digital, as opposed to analog, communication techniques, enabling more advanced digital signal processing features, such as frequency hopping, spread spectrum, forward error correction, etc.

A drawback of cordless telephones is that the capability to roam with the handset also creates the opportunity for a user to misplace the handset. For example, a user may roam within the user's home while engaged in a telephone conversation, and when the conversation is complete the user may simply put the handset down in any convenient spot. If the user becomes otherwise distracted, the user may forget where the user placed the handset when the user later desires to place a new outgoing telephone call. To address this problem, cordless telephones have developed a feature, typically referred to as the "page" or "handset locator" feature, whereby the user presses a page button on the base unit to cause the handset to provide an audible signal, typically a short three-"beep" signal.

A drawback of conventional page signals is that they are the same regardless of the environmental conditions. As the allowable range between the base and handset gets bigger, this can yield a problematic situation wherein the user cannot effectively employ the page feature since the user either cannot hear the short audible signal, or cannot accurately determine the source of the audible signal before it terminates. There is

therefore a need for a cordless telephone with an adaptive paging feature to adjust to the conditions so that a user can effectively locate a misplaced handset.

Summary of the Invention:

5 In one embodiment, a cordless telephone according to the invention includes a base unit, including a paging mechanism, and a handset, including an alerting mechanism responsive to the paging mechanism. At least one of the base unit and the handset includes a page adjusting mechanism to affect an alerting signal output from the alerting mechanism based on a condition. Thus, the paging signal is adaptive to increase the
10 opportunity for a user to determine the location of a misplaced handset.

 In another embodiment, a cordless telephone is equipped so that the base unit can provide an indication related to a distance between the base unit and the handset. In yet another embodiment, a cordless telephone is equipped so that the paging mechanism is adjusted based on user control.

15 In a further embodiment according to the invention, a method is provided for affecting an alerting signal output by an alerting mechanism of a cordless telephone handset. The method includes the steps sensing a condition, and affecting the alerting signal based on the sensed condition.

20 Brief Description of the Drawing:

 The advantages of the invention will be apparent to one of skill in the art upon review of the following detailed description in light of the drawings, wherein:

Figure 1 is a simplified block diagram of one embodiment of a cordless telephone according to the invention;

Figure 2 is an exemplary flowchart of operation of a cordless telephone according to the invention;

5 Figure 3 is another exemplary flowchart of operation of a cordless telephone according to the invention;

Figure 4 is another exemplary flowchart of operation of a cordless telephone according to the invention;

10 Figure 5 is a simplified block diagram of another embodiment of a cordless telephone according to the invention; and

Figure 6 is a simplified block diagram of another embodiment of a cordless telephone according to the invention.

Detailed Description:

15 Figure 1 is a simplified block diagram of a cordless telephone according to the invention. Cordless telephone 105 includes a base unit 107 and a handset 109. Base unit 107 includes a user input unit 111, such as a keypad, via which a user may initiate a page function, such as by pressing a particular key of the keypad. Handset 109 includes an alerting mechanism 113, such as a speaker, that will issue an alerting signal in response
20 to an indication that the user initiated the page function. According to the invention, at least one of the base unit 107 and the handset 109 includes a page adjusting mechanism, such as a function block in processor 115 (base unit 107) or processor 117 (handset 109), and the page adjusting mechanism affects the alerting signal based on a condition.

Base unit 107 also includes a telephone line interface 119 for coupling to a telephone line and hence to a network, such as to a public switched telephone network via a central office. Base unit 107 also includes a transmit/receive element 121 and an antenna 123 for RF communication with handset 109 via corresponding elements 125 and 127. The details of RF communication between base units and handsets of cordless telephones are well known to those of skill in the art and will not be discussed herein in detail. Transmit/receive elements 121 and 125 are intended to include all of the typical devices employed for this function.

Handset 109 also includes a user input unit 129, such as a keypad, a microphone 131 and a receiver 133. These elements also function primarily in conventional ways that are well known to those of ordinary skill in the art, and these traditional functions will not be discussed in detail.

Operationally, when the handset 109 is not coupled to base unit 107, and is misplaced, the user activates the page function by, for example, pressing a PAGE key that is part of user input unit 111. A paging mechanism functional block of processor 115 receives an indication of this activation from user input unit 111 by way of traditional conditioning elements and signal transmission media, and causes transmit/receive element 121 to output a particular signal over the RF link to handset 109. In handset 109, processor 117 reacts to the particular signal by activating alerting mechanism 113.

Processors 115 and 117 may be microprocessors or digital signal processors, such as the DSP 1609 available from Lucent Technologies. According to the invention, either processor 115 and/or processor 117 takes a conditional action during the aforementioned

process. For example, processor 115 may adjust the particular signal based on a condition, or processor 117 may adjust the signal provided to alerting mechanism 113 based on a condition.

One example of a condition upon which the processor(s) 115/117 may make such an adjustment is a receive signal strength indication (RSSI). Traditionally, DSPs in cordless telephones determine the received signal strength of the signals between the base and handset to determine whether to switch to a different communication channel for the RF link. Thus, those of skill in the art are familiar with this measure and are familiar with the fact that it provides an estimate of channel quality. Further, those of skill in the art are familiar with an axiom by which the signal strength tends to be indirectly related to the distance between the base unit and the handset. Thus, signal strength is a good estimate of this distance. The invention, in one embodiment, takes advantage of this known measure to adjust the alerting signal. In an alternative embodiment, averaging RSSI across many frequencies may be employed to improve the estimate.

An advantage of adjusting the alerting signal based on the received signal strength indication is that it enables the alerting signal to be louder, to last longer or to have particular tonal qualities (i.e. pitch) when the signal strength is low, thereby providing the user with a better opportunity to locate the misplaced handset. Received signal strength is used here as an example of a condition upon which to estimate the distance between the base unit 107 and the handset 109. This is purely by way of example and not of limitation. Any other measure that bears a relationship to the distance between the base unit 107 and the handset 109 may be employed.

For example, the amount of time it takes for a signal to travel from the base unit 107 to the handset 109 and/or from the handset 109 to the base unit 107, also known as the “signal delay” may be employed. Another exemplary measure is any error measure, such as cyclic redundancy check (CRC), that demonstrates an increase in the error ratio
5 based on lower channel quality, and hence provides an estimate of distance.

Also, it is possible to use multiple measures as estimates of the distance between base unit 107 and handset 109, and to follow an algorithmic approach to developing an estimate with a higher confidence level. For example, the distance estimate may be based on measures of signal strength (or signal delay, or error level) in both directions between
10 the base unit 107 and the handset 109. Further, it is possible to use both signal delay and received signal strength, or any other combination of measures, to develop the distance estimate.

Figure 2 is an exemplary operational flowchart according to the invention. Here, at step 202 the base unit 107 receives a page initiation signal, such as from a user pressing a particular key of user input unit 111. At step 204, a measure of a condition is made by either base unit 107 or handset 109, and at step 206 the alerting signal is
15 adjusted based on the measure. The ordering of the steps 202 and 204 is purely by way of example and not of limitation. It is, of course, possible for the measure to have been made prior to the receipt of the paging signal and stored, for example, in a register.

20 For example, either the base unit 107 or the handset 109 can make routine measurements during a telephone call, and the alerting signal may be set based on the presumption that the handset is located at the same place it was located when the telephone call was completed (for if the handset was returned to the base unit, a paging

operation would not be necessary). According to this example, if the page adjusting unit is in the base unit 107, then the base unit 107 will affect the particular signal based on the measure. In one example, the particular signal can inform the handset 109 of the distance estimate (or the actual measurement upon which the distance was estimated). In another
5 example, the particular signal can set the level of the alerting signal for the handset, either in terms of volume, duration, pitch, cadence, or any combination of these and any other alert signal characteristics.

According to another example, the handset 109 includes the page adjusting mechanism, and the base unit 107 merely informs the handset 109 of the paging activity in a traditional manner, whereby the particular signal is a traditional signal. In this case, the page adjusting mechanism of processor 117 may, for example, read a measure value from a register therein and adjust the alerting signal accordingly.

As mentioned earlier, it is also possible to take the measure based on the particular signal. For example, after receipt of the particular signal in step 202, the handset 109 can output a signal to base unit 107 which base unit 107 can measure, and/or
5 can receive a signal from base unit 109 which handset 107 can measure. These real time measures can then be utilized to determine the appropriate level(s) for the alerting signal.

It is of course also possible to use the particular signal as the measured signal. In this way, the handset 109 will receive the particular signal and recognize it as the signal
20 informing it to begin to issue an alerting signal, and will also measure the strength of the particular signal (or some other characteristic thereof - such as comparing the time of receipt to a time stamp thereon) and adjust the alerting signal based on this measure.

Figure 3 depicts one of the many alternative operational methods, wherein the page initiation signal is received at step 303, a signal is issued from the handset 109 to the base 107 and measured by the base 107 at step 305, and a second signal is issued from base 107 to handset 109 (perhaps informing handset 109 of the measure from step 305) at step 307. At step 309, processor 117 calculates an adjustment to the alerting signal, and at step 311 the alerting signal is adjusted.

Figure 4 depicts an alternative method of operation according to the invention, whereby a measure of ambient noise is employed, either alone or in combination with one of the aforementioned embodiments, to adjust the alerting signal. Here, the page initiation signal is received at step 402, and a measure of ambient noise is made at step 404. In one example, step 402 includes the issuance of the particular signal from base unit 107 to handset 109, and in response thereto, microphone 131 and receiver 133 are employed to capture a measurement of the ambient noise. This measure can then be employed to adjust the alerting signal in step 406.

For example, the alerting signal can be adjusted to exceed the ambient noise in volume by a particular amount. Alternatively, or additionally, the pitch or other qualities of the alerting signal can be selected so that they do not overlap with those of the ambient noise. In this way, the likelihood of the user hearing the alerting signal is improved. Further, the ambient noise measure may be employed to determine that another signal, other than an audible signal, should be produced. For this example, a telephone such as telephone 105' shown in Figure 5 can include a visual indicator, such as light emitting diodes (LEDs) 501 on handset 109'.

Figure 6 shows telephone 105'' in another embodiment according to the invention. Here, base unit 107' includes an LED 602 or other indicator that informs the user of the proximity of the handset 109 to the base unit 107'. In a simple example, based on received signal strength, signal delay, or another measure discussed above and
5 falling within the scope of the present invention, processor 115 causes LED 602 to be illuminated if handset 109 is estimated to be more than a threshold distance away from base unit 107'. For example, if the estimate is that handset 109 is more than 25 feet from base unit 107', then LED 602 is illuminated to inform the user that handset 109 is in a different room in the house, and the user should thus search a greater radius of area than
10 may otherwise have been intended.

Alternatively, the indicator may comprise a plurality of LEDs or some other form of scale that provides the user with a general indication of how far away the handset 109 is from base unit 107'. In yet another alternative embodiment, user input unit 111 may include a button which the user can activate that will instruct the handset 109 to maintain
15 the alerting signal until the user activates a button on the handset 109, and have the alerting signal vary its characteristics based, for example, on user programming. For example, the user can hold a page button in a depressed or active position and the volume of the alerting signal will increase proportionately with the length of time the button is depressed, such that the user can activate the page feature until the user can hear the
20 alerting signal. Alternatively, the characteristic such as volume can vary automatically, such as based on the amount of time elapsed since initiation.

Various novel embodiments are thus provided to improve the ability of a user to locate a misplaced cordless telephone handset. Upon reviewing the description of the

invention, various additional alternative embodiments and variations of the inventive concept will undoubtedly be evident to those of skill in the art, and these variations are of course intended to fall within the scope of the present invention. For example, although the inventive concepts are described with respect to cordless telephony, they are equally
5 applicable to other embodiments wherein a user may locate a misplaced item through use of a paging feature, such as the location of a misplaced television remote control.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
22